

### x86 Assembly Instructions

**ADD** Adds <source> to <dest>. <dest> may be a register or memory. <source> may be a register, memory or immediate value.

**CALL** Call a function and return to the next instruction when finished. <proc> may be a relative offset from the current location, a register or memory address.

**CMP** Compare <source> with <dest>. Similar to SUB instruction but does not modify the <dest> operand with the result of the subtraction.

**DEC** Subtract 1 from <dest>. <dest> may be a register or memory.

**DIV** Divide the EDX:EAX registers (64-bit divisor) by <divisor>. <divisor> may be a register or memory.

**INC** Add 1 to <dest>. <dest> may be a register or memory.

**JE** Jump if Equal (ZF=1) to <loc>.

**JG** Jump if Greater (ZF=0 and SF=OF) to <loc>.

**JGE** Jump if Greater or Equal (SF=OF) to <loc>.

**JLE** Jump if Less or Equal (SF<=OF) to <loc>.

**JMP** Jump to <loc>. Unconditional.

**JNE** Jump if Not Equal (ZF=0) to <loc>.

**JNZ** Jump if Not Zero (ZF=0) to <loc>.

**JZ** Jump if Zero (ZF=1) to <loc>.

**LEA** Load Effective Address. Gets a pointer to the memory expression <source> and stores it in <dest>.

**MOV** Move data from <source> to <dest>. <source> may be an immediate value, register, or a memory address. <dest> may be either a memory address or a register. Both <source> and <dest> may not be memory addresses.

**MOVZBL** Zero extend <source> to long and save in <dest>.

**MUL** Multiply the EDX:EAX registers (64-bit divisor) by <source>. <source> may be a register or memory.

**POP** Take a 32-bit value from the stack and store it in <dest>. ESP is incremented by 4. <dest> may be a register, including segment registers, or memory.

**PUSH** Adds a 32-bit value to the top of the stack. Decrements ESP by 4. <value> may be a register, segment register, memory or immediate value.

**ROL** Bitwise Rotate Left the value in <dest> by <count> bits. <dest> may be a register or

### What does a Linker do?

– Merges multiple relocatable (.o) object files into a single executable object file that can be loaded and executed by the loader.

– As part of the merging process, resolves external references. • External reference: reference to a symbol defined in another object file.

– Relocates symbols from their relative locations in the .o files to new absolute positions in the executable.

– Updates all references to these symbols to reflect their new positions. • References can be in either code or data

### Memory Management

Info

unt>	memory address. <count> may be immediate or CL register.
ROR <dest>, <count>	Bitwise Rotate Right the value in <dest> by <count> bits. <dest> may be a register or memory address. <count> may be immediate or CL register.
SHL <de st>, <co unt>	Bitwise Shift Left the value in <dest> by <count> bits. Zero bits added to the least significant bits. <dest> may be reg. or mem. <count> is imm. or CL.
SHR <dest>, <count>	Bitwise Shift Right the value in <dest> by <count> bits. Zero bits added to the least significant bits. <dest> may be reg. or mem. <count> is imm. or CL.
SUB <de st>, <so urce>	Subtract <source> from <dest>. <source> may be immediate, memory or a register. <dest> may be memory or a register. (source = dest)->ZF=1, (source > dest)->CF=1, (source < dest)->CF=0 and ZF=0
TEST <dest>, <sourc e>	Performs a logical OR operation but does not modify the value in the <dest> operand. (source = dest)->ZF=1, (source <> dest)->ZF=0.
XCHG <dest>, <sourc e>	Exchange the contents of <source> and <dest>. Operands may be register or memory. Both operands may not be memory.
XOR <dest>, <sourc e>	Bitwise XOR the value in <source> with the value in <dest>, storing the result in <dest>. <dest> may be reg or mem and <source> may be reg, mem or imm.

#### Cheatographer



**rwwagner90**  
[cheatography.com/rwwagner90/](http://cheatography.com/rwwagner90/)

#### Cheat Sheet

This cheat sheet was published on 23rd October, 2012 and was last updated on 23rd October, 2012.

#### Sponsor

**FeedbackFair**, increase your conversion rate today!  
 Try it free!  
<http://www.FeedbackFair.com>